

Product datasheet:

O-range ECON® 2 one-gang junction box, air-tight, Depth 48 mm

O-range ECON® 2 / 3 / 4 - gang junction boxes

- Air-tight design with sealing membranes
- Toolless cable and conduit entries
- Integrated cable retention of the NYM cable, self-locking of the conduit
- Standardised separation of individual installation openings using a bridge
- Can be combined with all O-range® programme applications

One-gang junction box, air-tight, as multiple box for 2 device inserts, for cavity wall installation.

Cavity wall box, designed as cavity wall device connection box in accordance with DIN EN 60670/VDE 0606 and DIN 49073, made of plastic, with air-tight design in accordance with DIN 18015-5, installation opening 2 x Ø 60 mm, installation opening 2 x Ø 68 mm, depth 48 mm, for panel thickness 7-40 mm, combination distance 71 mm, with 2 screw domes and 2 plus-minus device screws, Toolless entry for NYM cables and data cables as well as for conduits Ø 20/25 mm (2 x Ø 20/25 mm, 4 x Ø 20 mm, 1 x 3 x 1.5 mm², 1 x 3 x 2.5 mm² or 5 x 1.5 mm²), protection class IP 30 according to DIN EN 60529, flame-retardant according to DIN EN 60695 up to 850° C, for cavity wall installation



Assembly instructions



Certificates



Planning data

Article number:	9252-22
EAN:	4013456550889
Inner packing / Packaging quantity:	10 / 100
Price group:	121

Dimensions / Form

Product depth:	48 mm
Drill/cut hole Ø:	2x68 mm

Connections / Entries

Number of entries:	4
For conduit Ø:	25 mm

Assembly / Installation

Min. panel thickness:	7 mm
Panel thickness max.:	40 mm
Assembly type:	HW (drywall/lightweight construction)

Approvals / Certifications

VDE:	Yes
------	-----

With the O-range ECON® 2 / 3 / 4 - gang junction boxes, KAISER offers the perfect basis and especially easy processing for the fitting of all standard installation accessories in multiple combinations. Thanks to their large installation opening without a central separation, it is easy to wire multiple devices together and even makes possible the use of pre-wired installation accessories. If different electrical circuits – e. g. for supply and communication connections – are used within a combination, the individual accessory installation spaces can be separated easily and in a standardised way.

Product datasheet:

- Easy installation of pre-wired accessories without spatial separation
- Maximum flexibility when fixing accessories, generous tolerance compensation
- Standardised separation of individual installation openings using a bridge
- Complete assembly and installation with just one screwdriver
- Can be combined with all O-range® programme applications