

Product datasheet:

Components

- Suitable for expansion in Click-mate NXT and XL-plus distribution boards.
- Equipped with distribution blocks.
- Component width: 36 mm.

Article number:	↗ AT90232
EAN:	8712259536699
Packaging quantity:	3

ETIM Product classification: Bell transformer

Primary voltage:	230 V
Secondary voltage 1:	8 V
Secondary voltage 2:	
Secondary voltage 3:	
Secondary amperage 1:	1 A
Secondary amperage 2:	
Secondary amperage 3:	
Max. output power:	8 W
Max. output current:	1 A
Max. power loss:	
Type of transformer:	Standard bell ringing transformer
Surface mounting:	No
Flush-mounted installation:	No
Suitable for distribution board:	No
Length:	85 mm
Width:	35 mm
Height:	65 mm
Width in number of modular spacings:	2
Short-circuit protected:	No
Temperature protection:	No
With on/off switch:	No

With the Click-mate NXT you can easily put together your custom distribution boxes. You choose one of the cabinets from the basic range based on the space available in the meter cabinet or the required components. You can then add, remove or move specific components. For example, it is possible to place components that are subject to a long-term load, such as groups for PV installations or charging stations, 'freely'. Or to reserve free space for components for home automation or energy management systems.



Assembly instructions