

Product datasheet:

Extension boxes

Article number: **AT91524**

EAN: 8712259534169

Dimensions / Form

Product width: 220 mm

Product depth: 390 mm

Electrical Properties

Rated current: 40 A

Number of residual current circuit breakers 2P: 2

Total number of circuit breakers: 8

Main switch (xxA): No

Connection (1/3-phase): 1-phase

Grey groups: 4

ETIM Product classification: Small distribution board equipped

Mounting method: Surface mounted

Number of rows:

Number of phases: 1

Protection: Miniature-/earth leakage circuit breaker

Number of single-phase miniature circuit breakers (MCB):

Number of three-phase miniature circuit breakers (MCB):

Release characteristic:

Rated short-circuit breaking capacity I_{cn} according to EN 60898 at 230 V:

Power consumption:

Total number of groups: 8

Number of direct groups: 0

Number of light groups: 8

Number of groups behind earth leakage switch: 8

Number of earth leakage circuit breakers: 0

Number of earth leakage switches 30 mA: 2

Number of earth leakage switches 300 mA: 0

Number of arc fault detection devices AFDD: 0

Number of earth leakage circuit breakers/ AFDD:



Assembly instructions

Product datasheet:

Protection main switch:	No
Number of poles main switch:	
Main switch rated current:	
Protection incoming RCD:	No
Protection high integrity:	No
Protection split load:	No
Protection dual RCD:	No
Number of outgoing ways:	18
Suitable for data:	No
Cooker group:	None
Cooker group suitable as power current group:	No
With socket outlet:	No
With bell transformer:	No
Overvoltage protection:	No
Type of overvoltage protection device:	
Outgoing connections with connectors for plug-in building installation:	
With meter:	No
With N-disconnect slide:	
Connection type:	
Housing material:	Plastic
Degree of protection (IP):	IP20
Height:	390 mm
Built-in height:	
Width:	220 mm
Built-in width:	
Width in number of modular spacings:	24
Depth:	110 mm
Built-in depth:	
Extension possible:	No
Type of covering:	
With transparent cover:	No
Type of closure:	
Lockable:	No
Colour:	
RAL-number:	

Click-mate NXT distribution boxes without main switch. To expand existing installations.